

# Digital Multimeter

DM-97

**HTC**  
**INSTRUMENTS**

## Features :

- 3¾ Digital Multimeter
- 4000 Counts
- Large LCD Display with Auto/Manual Range
- No Power-OFF under natural operation
- Data Hold, Max. / Min. Value Hold
- Capacitance, Frequency / Duty Cycle, Temperature and Transistor Test



## Technical Data :

Basic Functions	Range	Basic Accuracy
DC Voltage	0.1mV ~ 1000V	±(0.5%+4)
AC Voltage	0.001V ~ 750V	±(0.8%+6)
DC Current	0.1uA ~ 20A	±(1.0%+5)
AC Current	0.1uA ~ 20A	±(1.5%+5)
Resistance	0.1Ω ~ 40MΩ	±(0.8%+1)
Capacitance	0.001nF ~ 200uF	±(3.5%+8)
Frequency	2Hz ~ 30MHz	±(0.5%+4)
Celsius	-40°C~1000°C	±(0.8%+4)

## Special Function :

Diode test	✓	Function Protection	✓
Transistor testing	✓	Input impedance	10MΩ
Continuity Buzzer	Lower 30Ω ±10Ω	Sampling Rate	3 times per second
Low Battery Display	Lower 2.4V	AC Frequency Response	40-400Hz
Auto Power OFF	Approx. 30 min.	Power	F3V AAA

- Standard Accessories : Test Leads, Holster, Manual, Temperature Probe TP-01
- Dimension : 185(H) x 93(W) x 35(D)mm

**HTC**  
**INSTRUMENTS**